# **EXPLORER XP SERIES** FINISHES AND FUNCTIONS


FINISHES AVAILABLE		
BHMA SYMBOL	US CODE	DESCRIPTION
605	US3	Polished Brass
606	US4	Satin Brass
609	US5	Antique Brass
612	US10	Satin Bronze
613	US10B	Oil Rubbed Bronze
619	US15	Satin Nickel
625	US26	Polished Chrome
626	US26D	Satin Chrome

Refer to price list for stock finishes and functions

## XP00 ICXP00 CXP00 ANSI: F109

## ENTRANCE / OFFICE LOCK

Turn / Push button locking. Pushing and turning button locks outside lever requiring use of key until button is manually unlocked. Pushing button locks outside lever until unlocked with key or inside lever is turned.



Pushing button in inside lever locks outside lever. Turning inside lever or operating key in outside lever releases button automatically. Closing door does not release button. Button cannot be fixed in lock position. Inside lever always free. Latch bolt automatically deadlocks when door is closed.

**ENTRANCE LOCK PUSH BUTTON** 



#### CLASSROOM LOCK

STOREROOM LOCK

lever is always fixed.

Dead locking latch bolt operated by lever from either side except when outside lever is locked from outside by key. When outside lever is locked, latch bolt is operated by turning inside lever.








#### EXIT LOCK CONNECTING ROOM WITH KEY Deadlocking latch bolt operated with key from inside only. Blank plate outside.

Dead locking latch bolt operated by key in

outside lever or by rotating inside lever. Outside

**DORMITORY / ASSISTED LIVING** Deadlocking latch bolt operated by lever from either side except when outside lever is locked by key or by push button on inside lever. Key in outside lever locks or unlocks outside lever. Outside key releases push button when locked from inside. Rotating inside lever or closing the door releases push button.


## DOOR PREPARATION





CAL-ROYA PRODUCTS, IN





## PATIO

Deadlocking latch bolt operated by lever from either side. Outside lever is locked by push button inside and unlocked by rotating inside lever or closing door.



## PRIVACY LOCK

Latch bolt operated by lever from either side. Outside lever is locked by push button inside and unlocked by emergency release outside. Turning inside lever or closing door releases push button.



## HOSPITAL PRIVACY LOCK

Latch bolt operated by lever from either side. Outside lever is locked by push button inside and unlocked by turning turn button. Turning inside lever or closing door releases push button.



### PASSAGE SET

Latch bolt operated by lever from either side at all times.



#### DUMMY LEVER

Single dummy trim for one side of door. Pull only.



EXIT LOCK Blank plate outside. Inside lever always unlocked.

#### HOW TO ORDER: For "XPRI " replace de

For "XPRL", replace design name. Example: XP00 entrance in "XPRL" is XPRL00.

**\*** "IC" Indicates function available with BEST, FALCON & ARROW Interchangeable Core.

"CXP" Indicates function available with clutch OTHER FUNCTIONS NOT LISTED AVAILABLE UPON REQUEST

